



PRODUCT SPECIFICATIONS

NAME: 1~60W 220~230VAC Emergency Ballast for LED T8

ORDER CODE#: SF04EB01.60

TYPE: LED Emergency Ballast
LED Emergency Driver
LED Emergency Conversion Kit

SUB-TYPE: LED Emergency Ballast

UPDATED: 2019-12-18

APPLICABLE FOR: LED Tube Light

FEATURES

- Constant current battery output
- LED charges status display
- Embed with a test button to inspect the emergency and routine lighting function.
- The intelligent system will automatically start the inverter on the emergency condition
- Adjust the suitable voltage for the system
- Comply with European standards EN 61 347-2-7 and certified by CE, EMC, LVD, RoHS, SAA, CCC
- Compatible with all of the LED fixtures
- It is optimized with an IC controlled dual rate charger for energy savings



SPECIFICATIONS

Driver Type LED Emergency Ballast

Support Lamps LED Tube Light

Battery Type Ni-Cd 4.0Ah, 12V

Dimmable No

Self-Test Ability No

Warranty 3 Years

Surge-Protection Yes

LED Indicator ϕ 5mm Green LED with
300mm Line, 26#

OPERATION SPECIFICATIONS

Output Power 1~60 Watt

Input Voltage 110-265V AC, 50HZ/60HZ

Output Voltage 220-230V AC

Charge Current 0.05C

Illumination Time 1-3 Hour


Recharge Time 24 Hours

Mode Switch Time <0.5 Sec

Disclaimer: Sanforce© reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.



WIRING DIAGRAM



PHYSICAL PROPERTIES

Weight	200 g/pcs
Dimension(mm)	217x40x30
Battery Dimension(mm)	300x66x34
Encasing Dimension(mm)	360x120x45

TEMPERATURE AND RATINGS

Ambient Temperature	-20 to 45°C
Operating Temperature	70°C
IP Rating with Casing	67

SERVICES AND WARRANTY

- Packaging Detail: Standard packaging with export carton or according to requirements.
- Delivery Detail: 7-10 working days for samples, 10-20 days for mass production.
- The warranty period is 3 years or above. According to national standards, a replacement is mandatory after constantly using for 3 years. During the warranty period, it can be replaced with any quality problems (except for man-made factors).
- Requires professional maintenance after emergency power installation, in case any abnormal condition happens, please maintenance in time or inform our company to send professionals to provide technical support.

NOTE

Nickel Metal Hydride (Ni Cd) Battery Shipping Regulations to comply with IATA provisions for air transporting nickel metal hydride batteries. Please visit the following site to learn more:
<https://www.iata.org/contentassets/b08040a138dc4442a4f066e6fb99fe2a/guidance-document-nickel-metal-hydride-batteries-en-201608.pdf>

Disclaimer: Sanforce© reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.





No.29, Longfeng Road, Xinsheng, Longgang District, Shenzhen City, China

Tech Support: 0755-89648670, 0755-84293891 Fax: 0755-89648671

Email: info@sanforce-tech.com

www.sanforce-tech.com